

Explanation of Amendments in the Claims:

1.(currently amended) A method of simultaneously synchronizing multiple input signals to multiple output signals, comprising:

communicating a plurality of signal pairs each comprising a clock input and a signal input;

providing a discrete-time phase detector, loop filter, and voltage controlled oscillator that together operate as a single discrete-time phase locked loop (PLL) in hardware for calculating an output signal from an input signal;

providing a control logic;

providing a context memory (RAM) for storing a history for each of the respective signal pairs;

and, upon receipt at the discrete-time phase detector of the clock signal of a respective one of the signal pairs, operating the control logic [:]

to retrieve from the context memory the history for the respective signal pair,

to enable the discrete-time PLL ~~phase-locked-loop~~ to calculate from the respective input signal a respective output signal thus defining a resulting history for the respective input signal,

and to store the resulting history in the context memory for use in subsequent calculations for the respective input signal pair.

wherein the PLL is arranged to carry out a calculation for each of the signal pairs;

and wherein the multiple input signals are simultaneously synchronized by effecting the calculations of the PLL at a rate such that every input signal pair is serviced.

2.(currently amended) The method according to Claim 1 wherein the context ~~Context~~ memory is arranged to store and retrieve a history from the loop filter and a history from the Voltage Controlled Oscillator of the discrete-time phase locked loop.

3.(currently amended) The method according to Claim 1 wherein there is provided a high speed clock signal which is supplied to the control logic to control routing of input signals to the discrete-time PLL ~~Phase Locked-Loop~~, retrieving of the history from the context ~~Context~~ memory RAM, writing of the history into the loop filter and voltage controlled oscillator ~~Voltage Controlled-Oscillator~~ registers of the discrete-time PLL, triggering of the discrete-time PLL ~~Phase Locked-Loop~~ stages, storing of the history from the loop filter and voltage controlled oscillator ~~Voltage Controlled-Oscillator~~ registers into the context ~~Context~~ RAM, and routing of the output signal to a respective output port.